



# Repeater (Hub) Bilingual 5 port FireWire B (IEEE 1394b)

## Description

The Delock repeater by IOI can be used to extend a FireWire connection. It serves to a signal amplification up to 4.5 m. Furthermore you can connect up to 4 more FireWire devices and use the repeater as Hub.

## Images



Ref.	61669
EAN	4043619616695
Country of origin	Taiwan
Customs tariff number	85176200

## Specification

- IOI item number: 1394R-B5
- 5 x FireWire B (IEEE 1394b) ports with jackscrew lock holes
- Every port is protected by one 1,35 A / 33 V fuse
- Chipset: TI TSB81BA3D
- Data transfer rate up to 800 Mb/s
- 1394 bus powered: DC: 8 V~30 V, max. 3 A
- DC power input connector: Walkman-type 2.0 mm DC Jack
- Dimensions (LxWxH): 9,2 cm x 6,2 cm x 2,1 cm
- Power consumption < 3 Watts

### System requirements

- A free FireWire B port

### Package content

- FireWire B repeater

### Package

- Box